



## **PDF Compressor Free Version**



# Pressure Reducing Valve with Pressure Gauge Pressure Regulator

 Pressure Gauge Option - Bourdon tube Compact Pressure Gauge Battery Operated Digital Display Gauge Dual LCD Display Pressure Sensor Switch

Analog Display is readable from the side by a special scale.


Push-lock type of Knob is easy to handle.

Display is readable from the side by a special scale.

Knob position is selectable.

Pressure Reducing Valve

## Regulator



## Specifications of Pressure Regulator

Port DBF Compressor I	Free Version c1/4 (02)	Rc3/8 (02)
Fluid Medium	Air	
Max. Operating Pressure	145psi (1MPa)	
Pressure Setting Range	7.25 ~ 123.25psi (0.05 ∼ 0.85MPa)	
Pressure Resistance	181psi (1.2MPa)	
Operating Temp. Range	41~ 122°F (	5 ~ 50°C)

\* Rc is same as BSPT female thread

### Specifications of Bourdon Tube Pressure Gauge

Model Code	GK 46-B20
Fluid Medium	Air
Pressure Display Range	0  ~ 145psi (0 $\sim$ 1MPa)
Accuracy	± 5%F.S.

## Specification of Digital Pressure Gauge

Rated pressure range	0.000 ~ 1.000MPa
Pressure display range	-0.100 ~ 1.000MPa(%1、%2)
Proof pressure	217psi (1.5MPa)
Fluid medium	Air, non-corrosive / non-flammable gas
Battery type	CR 2032 Lithium battery (*4)
Battery life	About 3 years (at 5times indication/ day)
Low-power indicator	Yes
Battery replacement	Yes
Turn-on interval	60 seconds
Sampling rate	2Hz(2 times ⁄ sec.)
Repeatability	$\leq \pm 0.2\%$ F.S. $\pm 1$ digit
LCD display	7 segment, 3.5digit
Indicator accuracy	±2%F.S. ±1digit or below(ambient temp. ∶at 77± 5.4°F (25 ± 3°C))
Protective structure	IP65 (*3)
Ambient temp. range	Operation: 32~122°F (0~50°C), Storage: 14~140°F (-10 ~ 60°C) (No dew condensation, no freezing)
Ambient humidity range	Operation / Storage: 35 ~ 85%RH (No dew condensation)
Vibration proof	Total amplitude 1.5mm or 100m/s <sup>2</sup> , 10Hz-55Hz-10Hz scan for 1minute, Direction of X, Y and Z for 2hours each
Shock resistance	100m/s², 3 times each direction of X, Y and Z
Temperature characteristic	±2%F.S. of detected pressure at 77°F (25°C)

\*1. The display at the time of impressing negative pressure will be Fig.1, and Fig. 2.


\*2. Indicator accuracy is not guaranteed for the pressure range -0.1 ~ 0Mpa.

\*3. Air tube must be inserted into the atmospheric release port to maintain IP65. See Fig.3.

\*4. Using other battery can result in electrical shock or fire.

\*5. This digital pressure gauge can not be calibrated. So the reading could be out of tolerance with time.






Atmospheric release port / Fig 3

Specif	fications of D	ual LCD Digital Pres	sure Sensor	
Sensor t	<b>DF Compress</b> ype	or Free Version SEU-31-N	SEU-32-N	SEU-32-P
	ressure range		0.000~1.000MPa	
Proof pr	essure		1.5MPa	
Fluid me	edium	Air, No	n-corrosive / Non-flammal	ble gas
Power re	equirements	DC12	$2V \sim 24V$ (Ripple $\pm 10\%$ o	or less)
	consumption	2	40mA or less(With no loa	d)
	Switch output	NPN open	collector	PNP open collector
Switch	Max. load current		125mA	
output	Max. supply voltage	DC3	30V	DC24V
	Residual voltage		1.5V or below	
Repeata	bility		±0.2% F.S. ±1 digit or le	ss
	One point set mode			
Hysteresis	Hysteresis mode		Adjustable (※)	
	Window comparator mode			
Respons	se time	2.5ms or less (Chattering-proof f	ering-proof function: 25ms, 100ms, 250ms, 500ms, 1000ms, 1500ms selections	
Output sh	nort circuit protection	<u> </u>	Yes	
Digital d	lisplay	3 colors (Red, Green,	Orange) indication (Sampl	ling rate: 5times / 1sec.)
Indicato	r accuracy	±2%F.S. ±1digi	t or below (at Ta= 77± 5.4	°F (25 ± 3°C))
Switch C	DN indicator		Orange 1 & 2 indicator	
Analog o (Voltage	output e output)		$1 \sim 5V \pm 2.5\%$ F.S. (within rated pressure range) $\pm 1$ % F. S. or less, output impedance 1k $\Omega$	
	Protective structure	· _	IP40	•
	Ambient temp. range	Operation: 32~122°F (0~50°C),	Storage: 14~140°F (-10 ~ 60°C) (N	No dew condensation, no freezing
	Ambient humidity range	Operation / Sto	orage: 35 ~ 85%RH (No de	w condensation)
Environment	Withstand voltage	1000VAC in 1 min. (Between case and lead wire)		
	Insulation resistance	50MΩ o rmore	(500VDC) (Between cas	e and lead wire)
	Vibration proof	Total amplitude1.5mm or 100m/	$\rm s^2$ 、10Hz $\sim$ 150Hz $\sim$ 10Hz for 1r	min. 、2 hrs. each direction X, Y, Z
	Shock resistance	100m/	s <sup>2</sup> 3 times each in direction	i X, Y, Z
-	nperature characteristics $\pm 2\%$ F.S. or less at Ta=77°F(25°C), temp. range 32~122°F (0~50°C)		$32 \sim 122^{\circ} E (0 \sim 50^{\circ} C)$	
Tempera	ture characteristics	±∠/01.0.011€55 at 1a	-11 i (25 C), temp. range	$32^{-1}22^{-1}(0^{-5}0^{-5}0^{-5})$

%. Hysteresis value is adjustable within 1~8 digits for one point set mode and window comparator mode.






## ▲ Detailed Safety Instructions |

Before using PISCO products, be sure to read "Safety Instructions" and "Safety Instruction Manual" and Common Safety Instructions for Modular Filter and Regulator Unit".

### Caution

 When discharging secondary side air open to atmosphere, sympathetic vibration may be generated by an influence of a flow. Because there is a danger of causing such as the internal damage, please avoid the use such as discharging secondary side air open to atmosphere for long period of time.






would coue	Port size : 02(Rc1/4)	Port size : 03(Rc3/8)	File
RVF300- 🗌 - 🗌	465.5	444.5	CRM-002

\* Fill in 
on left with "02" for Rc1/4 or "03" for Rc3/8.

Fill in the end 🗌 with "R" for the flow direction from right to left. Leave the end 🗌 blank when the direction is from left to right.

## RVF Regulator with Bottom Knob and Bourdon Tube Pressure Gauge


RoHS compliant



Madal Cada	Weight (g)	
Model Code	Port size : 02(Rc1/4)	Port size : 03(Rc3/8)
RVF300- 🗌 - 🗌 S	465.5	444.5

\* Fill in  $\Box$  on left with "02" for Rc1/4 or "03" for Rc3/8.


Fill in the end 🗌 with "R" for the flow direction from right to left. Leave the end 🗌 blank when the direction is from left to right.



Model code	Weight (g)	
	Port size : 02(Rc1/4)	Port size: 03(Rc3/8)
RVF300-①-②G	474	453

## RVF Regulator with Bottom Knob and Digital Pressure Gauge

RoHS compliant




Digital pressure gauge : GPD

Model Code	Weight (g)	
Model Code	Port size : 02(Rc1/4)	Port size : 03(Rc3/8)
RVF300-①-②SG	474	453

%1. The dimension of 103.5mm is just for reference. The actual distance might be slightly different.

%2. Fill in ① of model code with 02 for Rc1/4 thread or 03 for Rc3/8 thread.

Fill in 2 with R only if the flow direction from right to left is needed. Otherwise leave it blank (standard flow direction is from left to right).



●For model codes with T2 □ and T3 □

Model Code	Weight (g)	
	Port size : 02(Rc1/4)	Port size: 03(Rc3/8)
RVF300-①-②T□	510	489
RVF300-①-②T□C	473	452

Fill in 🗌 with 2 if SW 1point output + analog output pressure sensor is needed and 3 for SW 2points output pressure sensor.


### ●For model codes with T4 □ and T5 □

Model Code	Weight (g)	
Model Code	Port size : 02(Rc1/4)	Port size : 03(Rc3/8)
RVF300-①-②T□	517	496

Fill in 🗌 with 4 if NPN output, SW 2points output+analog output pressure sensor is needed, 4P for PNP output, SW 2points output+analog output sensor, 5 for NPN output, SW 2points output+copy function sensor and 5P for PNP output, SW 2points output+copy function sensor.

- % 1. The dimensions of 105.9mm and 106.8mm are just for reference.
- % 2. The Cable length of M8, 4 pin connector is 150mm
- % 3. Fill in (1) of model code with 02 for Rc1/4 thread or 03 for Rc3/8 thread.

Fill in 2 with R only if the flow direction from right to left is needed. Otherwise leave it blank (standard flow direction is from left to right).



## RVF Begulator with Bottom Knob and Dual LCD Digital Pressure Sensor

●For model codes with T2 □ and T3 □

Model Code	Weight (g)	
	Port size : 02(Rc1/4)	Port size: 03(Rc3/8)
RVF300-①-②ST□	510	489
RVF300-①-②ST□C	473	452

Fill in 🗌 with 2 if SW 1point output+analog output pressure sensor is needed and 3 for SW 2points output pressure sensor.

●For model codes with T4 □ and T5 □

Model Code	Weight (g)	
Model Code	Port size : 02(Rc1/4)	Port size : 03(Rc3/8)
RVF300-①-②ST□	517	496


Fill in  $\Box$  with 4 if NPN output, SW 2points output+analog output pressure sensor is needed, 4P for PNP output, SW 2points output+analog output sensor, 5 for NPN output, SW 2points output+copy function sensor and 5P for PNP output, SW 2points output+copy function sensor.

- % 1. The dimensions of 105.9mm and 106.8mm are just for reference.
- % 2. The Cable length of M8、4 pin connector is 150mm
- % 3. Fill in (1) of model code with 02 for Rc1/4 thread or 03 for Rc3/8 thread.

Fill in 2 with R only if the flow direction from right to left is needed. Otherwise leave it blank (standard flow direction is from left to right).



## REVE) Regulator with Top Knob and No Gauge



\* Fill in  $\square$  on left with "02" for Rc1/4 or "03" for Rc3/8.

Fill in the end 🗌 with "R" for the flow direction from right to left. Leave the end 🗌 blank when the direction is from left to right.


## Regulator with Bottom Knob and No Gauge


**RoHS** compliant 2-Rc1/4 1.5 53 67 1.5 2-Rc3/8 <u>ത്</u> IN = cΩ, 101 R N N. 2-6.5  $M42 \times 1.5$ H50 2-8 2.3 53 40 35 28 RVF300- - SL 429 408

\* Fill in 
on left with "02" for Rc1/4 or "03" for Rc3/8.

Fill in the end 🗌 with "R" for the flow direction from right to left. Leave the end 🗌 blank when the direction is from left to right.

## Characteristics





#### Chemical Classification Chemicals Applications Type PDF Free Version Compress Metal picking solution, acid Acid degreasing solution, skin repair Fluorine, Phosphoric Acid, Chromic Acid and etc. solution and etc. Inorganic Caustic Soda, Caustic Potash, Slaked Lime, Compound Alkaline degreasing solution for Alkali Aqueous Ammonia, Washing Soda and other Alkali metals Materials Sodium Sulphide, Potassium Nitrate, Potassium Inorganic Salt Dichromate, Sodium Nitrate and etc. Aromatic Benzene, Toluene, Xylene, Ethylbenzene, Styrene Contained in painting thinner Hydrocarbon and etc. (Benzene, Toluene and Xylene) Methyl Chloride, Ethylene Chloride, Methylene Organic solvent solution for Chlorinated Chloride, Acetylene Chloride, Chloroform, metals (Trichloroethylene. Aliphatic Trichloroethylene, Berkelene, Carbon Tetrachloride Berkeleneand Carbon Hvdrocarbon and etc. Tetrachloride) Chlorinated Chlorobenzene, Dichlorobenzene, Benzene Aromatic Agricultural Chemicals Hexachloride (BHC) and etc. Hydrocarbon Petroleum Solvent, Naphtha and Gasoline Components Methyl Alcohol, Ethyl Alcohol, Cyclohexanol and Alcohol Used as an anti-freezing agent Benzyl alcohol Fenol Carbolic Acid, Cresol, Naphthol and etc Disinfectant Break fluid additives Ether Methyl Ether, Ethyl Methyl Ether and Ethyl Ether Organic Acetone, Methyl Ethyl Ketone, Cyclohexanone, Compound Ketone Acetophenon and etc. Dyeing agent and oxalic acid Formic Acid, Acetic Acid, Butylic Acid, Acrylic Acid, are used for aluminum repairing Carboxylic Acid Oxalic Acid. Phthalic Acid and etc. agent. Phthalic acid is used for base of paint. Used as additives of lubricant. Dimethyl Phthalate (DMP), Diethyl Phthalate synthetic hydraulic fluid or rust Phosphate (DEP), Dibutyl Phthalate (DBP) and Dioctyl inhibitor. Also used as plasticizer Phtalate (DOP) for synthetic resins. Glycolic Acid, Lactic Acid, Malic Acid, Citric Acid Oxo Acid and Tartaric Acid Nitro Nitromethane, Nitroethane, Nitroethylene, Compound Nitrobenzene and etc. Methyl Amine, Dimethyl Amine, Ethylamines, Amine Break fluid additives Aniline, Acetaniline and etc. Acetonitrile, Acrylonitrile, Benzonitrile, aceto(iso) Nitrile Material of nitrile rubber nitrile and etc.

### List of Chemical Resistance (Do not use the product under the following chemical atomosphere)

## ▲ Operation of Regulator

### Pressure Setting Procedure

- $\textcircled{\sc l}$  Pull Handle up to unlock before the pressure adjustment.
- O Turn Handle right to increase pressure and left to decrease.

Note) Pressure adjustment needs to be done by turning Handle in the clockwise (in the direction of increasing pressure).

3 After the adjustment is completed, make sure to push Handle down to lock it.



# Gommon Safety Instructions for Modular Type Filter and Regulator Unit

Before selecting or using PISCO products, read the following instructions. Read the detailed instructions for individual series.

## \land Warning

- 1. When installing the dryer, provide adequate support and fix it securely. Looseness or dropping off of the dryer may cause injuries.
- 2. Do not use the dryer without the explosion-proof casing (bowl guard). If the bowl breaks, the pieces may fly apart to cause injuries.
- 3. Make sure to set the lock lever on the filter, mist filter and micromist filter to "lock" before using. Otherwise, there is a risk of Bowl Guard or Bowl coming off which may cause injuries.
- 4. When conducting the maintenance, checkup, or replacement of the product, make sure to turn off the power and shut off the air supply. Confirm the residual pressure in the piping becomes zero before maintenance or replacement of expendables.
- 5. Do not use the dryer in a fluid or atmosphere containing corrosive gas or organic solvent gas. Such a use may deteriorate the dryer body which causes leakage or damage.

## ▲ Caution |

1. Air Filter, Mist filter and Micromist Filter shall be installed downward in a vertical direction. Improper installation may cause faulty draining.

2. Drain in Air Filter, Mist Filter and Micromist Filter are discharged automatically at the air pressure less than 0.05MPa for the manual drain type and 0.15MPa for the auto drain type. When installing, consider the self-discharging of air and drain.

3. When the manual drain type is selected, discharge drain before it reaches to the "MAX. DRAIN LEVEL" . Otherwise, it may become the cause which the drain flows into a secondary side.

4. Check the IN side of air supply by the  $\triangleright\,\text{mark}.$  Wrong piping may impair the performance.

5. Do not apply the pressure beyond the pressure setting range (Max. 0.85MPa) for Regulator. Otherwise, there is a risk of malfunctions.

# ▲ SAFETY Instructions

## PDF Compressor Free Version

This safety instructions aim to prevent personal injury and damage to properties by requiring proper use of PISCO products.

Be certain to follow ISO 4414 and JIS B 8370

ISO 4414 : Pneumatic fluid power···Recomendations for the application of equipment to transmission and control systems.

 $\mathsf{JIS} \ \mathsf{B} \ \mathsf{8370}$  : General rules and safety requirements for systems and their components.

This safety instructions is classified into "Danger", "Warning" and "Caution" depending on the degree of danger or damages caused by improper use of PISCO products.

**Danger** Hazardous conditions. It can cause death or serious personal injury.

Warning Hazardous conditions depending on usages. Improper use of PISCO products can cause death or serious personal injury.

Azardous conditions depending on usages. Improper use of PISCO products can cause personal injury or damages to properties.

## \land Warning I

## 1. Selection of pneumatic products

- ① A user who is a pneumatic system designer or has sufficient experience and technical expertise should select PISCO products.
- ② Due to wide variety of operating conditions and applications for PISCO products, carry out the analysis and evaluation on PISCO products. The pneumatic system designer is solely responsible for assuring that the user's requirements are met and that the application presents no health or safety hazards. All designers are required to fully understand the specifications of PISCO products and constitute all systems based on the latest catalog or information, considering any malfunctions.
- 2. Handle the pneumatic equipment with enough knowledge and experience
  - Improper use of compressed air is dangerous. Assembly, operation and maintenance of machines using pneumatic equipment should be conducted by a person with enough knowledge and experience.
- 3. Do not operate machine / equipment or remove pneumatic equipment until safety is confirmed.
  - Make sure that preventive measures against falling work-pieces or sudden movements of machine are completed before inspection or maintenance of these machine.
  - ② Make sure the above preventive measures are completed. A compressed air supply and the power supply to the machine must be off, and also the compressed air in the systems must be exhausted.
  - ③ Restart the machines with care after ensuring to take all preventive measures against sudden movements.



Disclaimer 🔳

- 1. PISCO does not take any responsibility for any incidental or indirect **PSE**. Compression Frequencies, loss of benefits, personal injury, etc., caused by any failure on use or application of PISCO products.
- 2. PISCO does not take any responsibility for any loss caused by natural disasters, fires not related to PISCO products, acts by third parties, and intentional or accidental damages of PISCO products due to incorrect usage.
- 3. PISCO does not take any responsibility for any loss caused by improper usage of PISCO products such as exceeding the specification limit or not following the usage the published instructions and catalog allow.
- PISCO does not take any responsibility for any loss caused by remodeling of PISCO products, or by combinational use with non-PISCO products and other software systems.
- 5. The damages caused by the defect of Pisco products shall be covered but limited to the full amount of the PISCO products paid by the customer.

# ▲ SAFETY INSTRUCTION MANUAL

PDF Compressor Free Version PISCO products are designed and manufactured for use in general industrial machines. Be sure to read and follow the instructions below.

## \land Danger 🔳

- 1. Do not use PISCO products for the following applications.
  - ① Equipment used for maintaining / handling human life and body.
  - ② Equipment used for moving / transporting human.
  - ③ Equipment specifically used for safety purposes.

## ▲ Warning I

- 1. Do not use PISCO products under the following conditions.
  - Beyond the specifications or conditions stated in the catalog, or the instructions.
  - ② Under the direct sunlight or outdoors.
  - ③ Excessive vibrations and impacts.
  - ④ Exposure / adhere to corrosive gas, inflammable gas, chemicals, seawater, water and vapor. \*
     \* Some products can be used under the condition above(④), refer to the details of specification and condition of each product.
- 2. Do not disassemble or modify PISCO products, which affect the performance, function, and basic structure of the product.
- 3. Turn off the power supply, stop the air supply to PISCO products, and make sure there is no residual air pressure in the pipes before maintenance and inspection.
- 4. Do not touch the release-ring of push-in fitting when there is a working pressure. The lock may be released by the physical contact, and tube may fly out or slip out.
- 5. Frequent switchover of compressed air may generate heat, and there is a risk of causing burn injury.
- 6. Avoid any load on PISCO products, such as a tensile strength, twisting and bending. Otherwise, there is a risk of causing damage to the products.
- 7. As for applications where threads or tubes swing / rotate, use Rotary Joints, High Rotary Joints or Multi-Circuit Rotary Block only. The other PISCO products can be damaged in these applications.
- 8. Use only Die Temperature Control Fitting Series, Tube Fitting Stainless SUS316 Series, Tube Fitting Stainless SUS316 Compression Fitting Series or Tube Fitting Brass Series under the condition of over 60°C (140° F) water or thermal oil. Other PISCO products can be damaged by heat and hydrolysis under the condition above.
- 9. As for the condition required to dissipate static electricity or provide an antistatic performance, use EG series fitting and antistatic products only, and do not use other PISCO products. There is a risk that static electricity can cause system defects or failures.
- 10. Use only Fittings with a characteristic of spatter-proof such as Antispatter or Brass series in a place where flame and weld spatter is produced. There is a risk of causing fire by sparks.
- 11. Turn off the power supply to PISCO products, and make sure there is no residual air pressure in the pipes and equipment before maintenance. Follow the instructions below in order to ensure safety.
  - ① Make sure the safety of all systems related to PISCO products before maintenance.
  - ② Restart of operation after maintenance shall be proceeded with care after ensuring safety of the system by preventive measures against unexpected movements of machines and devices where pneumatic equipment is used.
  - ③ Keep enough space for maintenance when designing a circuit.
- 12. Take safety measures such as providing a protection cover if there is a risk of causing damages or fires on machine / facilities by a fluid leakage.




## ▲ Caution ■


- 1. Remove dusts or drain before piping. They may get into the peripheral **Macion preside environment** malfunction.
- 2. When inserting an ultra-soft tube into push-in fitting, make sure to place an Insert Ring into the tube edge. There is a risk of causing the escape of tube and a fluid leakage without using an Insert Ring.
- 3. The product incorporating NBR as seal rubber material has a risk of malfunction caused by ozone crack. Ozone exists in high concentrations in static elimination air, clean-room, and near the high-voltage motors, etc. As a countermeasure, material change from NBR to HNBR or FKM is necessary. Consult with PISCO for more information.
- 4. Special option "Oil-free" products may cause a very small amount of a fluid leakage. When a fluid medium is liquid or the products are required to be used in harsh environments, contact us for further information.
- 5. In case of using non-PISCO brand tubes, make sure the tolerance of the outer tube diameter is within the limits of Table 1.

mm size	Nylon tube	Polyurethane tube	inch size	Nylon tube	Polyurethane tube			
Ø1.8mm	_	$\pm$ 0.05mm	Ø1/8	$\pm$ 0.1mm	$\pm$ 0.15mm			
Ø3mm	—	$\pm$ 0.15mm	Ø5/32	$\pm$ 0.1mm	$\pm$ 0.15mm			
Ø4mm	$\pm$ 0.1mm	± 0.15mm	Ø3/16	$\pm$ 0.1mm	$\pm$ 0.15mm			
Ø6mm	$\pm$ 0.1mm	$\pm$ 0.15mm	Ø1/4	$\pm$ 0.1mm	± 0.15mm			
Ø8mm	± 0.1mm	± 0.15mm	Ø5/16	$\pm$ 0.1mm	± 0.15mm			
Ø10mm	$\pm$ 0.1mm	$\pm$ 0.15mm	Ø3/8	$\pm$ 0.1mm	± 0.15mm			
ø12mm	$\pm$ 0.1mm	± 0.15mm	Ø1/2	$\pm$ 0.1mm	± 0.15mm			
Ø16mm	± 0.1mm	± 0.15mm	Ø5/8	$\pm$ 0.1mm	± 0.15mm			

● Table 1. Tube O.D. Tolerance

- 6. Instructions for Tube Insertion
  - ① Make sure that the cut end surface of the tube is at right angle without a scratch on the surface and deformations.
  - ② When inserting a tube, the tube needs to be inserted fully into the pushin fitting until the tubing edge touches the tube end of the fitting as shown in the figure below. Otherwise, there is a risk of leakage.





Tube is not fully inserted up to tube end.

- ③ After inserting the tube, make sure it is inserted properly and not to be disconnected by pulling it moderately.
- \*\*. When inserting tubes, Lock-claws may be hardly visible in the hole, observed from the front face of the release-ring. But it does not mean the tube will surely escape. Major causes of the tube escape are the followings;

① Shear drop of the lock-claws edge

② The problem of tube diameter (usually small)

Therefore, follow the above instructions from to , even lock-claws is hardly visible.

- 7. Instructions for Tube Disconnection
  - ① Make sure there is no air pressure inside of the tube, before disconnecting it.
  - Pupp the release ting of the sush-in fitting evenly and deeply enough to pull out the tube toward oneself. By insufficient pushing of the releasering, the tube may not be pulled out or damaged by scratch, and tube shavings may remain inside of the fitting, which may cause the leakage later.
- 8. Instructions for Installing a fitting
  - ① When installing a fitting, use proper tools to tighten a hexagonal-column or an inner hexagonal socket. When inserting a hex key into the inner hexagonal socket of the fitting, be careful so that the tool does not touch lock-claws. The deformation of lock-claws may result in a poor performance of systems or an escape of the tube.
  - ② Refer to Table 2 which shows the recommended tightening torque. Do not exceed these limits to tighten a thread. Excessive tightening may break the thread part or deform the gasket and cause a fluid leakage. Tightening thread with tightening torque lower than these limits may cause a loosened thread or a fluid leakage.
  - ③ Adjust the tube direction while tightening thread within these limits, since some PISCO products are not rotatable after the installation.

●Table 2:	Recommended	tightening	torque /	Sealock	color /	Gasket
materials	6					

Thread type	Thread size	Tightening torque	Sealock color	Gasket materials	
Metric thread	M3  imes 0.5	0.7N <sup>.</sup> m		SUS304 NBR	
	M5  imes 0.8	1.0 ~ 1.5N∙m			
	M6  imes 1	2 ~ 2.7N <sup>.</sup> m			
	M3  imes 0.5	0.5 ~ 0.6N·m —			
	M5  imes 0.8	1 ~ 1.5N <sup>.</sup> m		РОМ	
	M6  imes 0.75	0.8 ~ 1N <sup>.</sup> m			
	M8  imes 0.75	1 ~ 2N·m			
Taper pipe thread	R1/8	7 ~ 9N∙m			
	R1/4	12 ~ 14N·m	White		
	R3/8	22 ~ 24N·m			
	R1/2	28 ~ 30N·m			
Unified thread	No.10-32UNF	1.0 ~ 1.5N <sup>.</sup> m	—	SUS304、NBR	
National pipe thread taper	1/16-27NPT	7 ~ 9N·m			
	1/8-27NPT	7 ~ 9N∙m		_	
	1/4-18NPT	12 ~ 14N m	White		
	3/8-18NPT	22 ~ 24N·m			
	1/2-14NPT	28 ~ 30N·m			

\* These values may differ for some products. Refer to each specification as well.

### 9. Instructions for removing a fitting

- When removing a fitting, use proper tools to loosen a hexagonal-column or an inner hex bolt.
- ② Remove the sealant stuck on the mating equipment. The remained sealant may get into the peripheral equipment and cause malfunctions.
- 10. Arrange piping avoiding any load on fittings and tubes such as twist, tensile, moment load, shaking and physical impact. These may cause damages to fittings, tube deformations, bursting and the escape of tubes.